

Power Valve Output-stage in two or three valve sets or first stage low frequency if followed by transformer coupled UD 2



ZD 2

Filament voltage 3 Volts
 Filament current 0.14 Amps
 Slope 1 mA/V
 Amplification factor 6.2
 Impedance 6,200 Ohms
 Max. Plate voltage 150 Volts

V_a	V_g
50	-4.5
100	-9
150	-13.5

The ratio of the L. F. transformer in your set should not be too high.