#### TRIODE THYRATRON

## XRI-1600A

1.6 amp triode, inert gas-filled thyratron with negative control characteristic. Primarily designed for industrial control applications.

#### PRELIMINARY DATA

This data sheet should be read in conjunction with DEFINITIONS AND GENERAL OPERATIONAL RECOMMENDATIONS - THYRATRONS, which precede this section of the handbook.

#### LIMITING VALUES (absolute ratings, not design centre)

It is important that these limits are never exceeded and such variations as mains fluctuations, component tolerances and switching surges must be taken into consideration in arriving at actual valve operating conditions.

Maximum peak anode voltage		
Inverse	1.5	kΥ
Forward	1.5	kV
Maximum cathode current Normal service		
Peak (25c/s and above)	20	. А
Average (max. averaging time 15s)	1.6	A
Ignitor firing service (Filament voltage = 2.75V)		
Peak	30	A
Average	0.5	A
Maximum negative grid voltage		
Before conduction	250	V
During conduction	10	٧
Maximum positive grid current during the time that the anode voltage is more positive than -10V		
Peak	1.25	· A
Average (averaged over 1 cycle)	100	mA
Maximum peak positive grid current during the time that the anode voltage is more negative		
than -10V	5.0	mA
Maximum grid resistor	100	kΩ
Minimum valve heating time	10	s
Maximum commutation factor	10	
Maximum ambient temperature	+70	°C



## XRI-1600A

## TRIODE THYRATRON

#### **CHARACTERISTICS**

#### Electrical

*Filament voltage	2.5	V
*Filament current at 2.5V		
Maximum	9.5	À
Average	8.5	Α
Anode to grid capacitance	350	. mpF
Grid to cathode capacitance	10	pF
Recovery (deionisation) time (approx.)		
$V_g = -250V$	200	μς
$V_g = -100V$	300	μs
lonisation time (approx.)	10	μ\$
Anode voltage drop (approx.)	10	٧
Critical grid current at $V_a = 1.5kV$	<20	μА
*These ratings apply for normal service.*		
For ignitor firing service, the following ratings apply:		
Filament voltage	2.75	٧

Average 9.2 A
When two or more valves are used with one filament transformer, the centre-tap of the filament transformer must be used for the circuit returns. This may also be connected to the filament centre-taps.

#### Mechanical

Filament current at 2.75V

Maximum


Type of cooling	, Convection	
Recommended mounting position	Any between horizontal and vertical with base down	
Maximum net weight	{115 g 4.1 oz	
Weight of valve in carton	{275 g 9.7 oz	
Dimensions of packing	$\begin{cases} 3.5 \times 3.5 \times 8.5 & \text{in} \\ 89 \times 89 \times 215 & \text{mm} \end{cases}$	

The anode structure must be left free to ensure adequate cooling by free conduction.




10.3

# XRI-1600A




## TRIODE THYRATRON

# XRI-1600A



CONTROL CHARACTERISTIC





GRID ION CURRENT CHARACTERISTIC

OCTOBER 1959 (1)

Page C2